

# SHENZHEN FUDIANKANG ENERGY CO., LTD

Tel:86-13729889887 Fax:86-20-84550026

Web: www.fdkenergy.com Email: info@fdkenergy.com

### **DATA SHEET**

**DIESEL GENERATOR 2000KW** MODEL#FDK-CG2000N/H2 650HZ/1800RPM **CUMMINS MODEL: QSK60-G4** 



#### **General Features:**

- All qualified generator sets are subjected to a comprehensive performance test which includes 50% load, 70% load, 100% load, 110% load and to check, verify that all control systems, alarm and shut-down protection.
- Equipped with battery charger and 24V high performance maintenance-free lead-acid starting batteries and connecting
- Stainless galvanized zinc plates with strong corrosion-proof.
- Vibration isolators between the engine/alternator and base frame.
- Equipped with industrial silencer and flexible exhaust hose.
- Designed to comply with ISO8528/GB2820.
- Powered by Cummins engine and coupled with Stamford alternator.
- Water jacket preheater, oil heater and double air cleaner, etc. are available.

#### **FDK Diesel Generator Set Data**

Genset Model	FDK-CG2000N/H2
Prime Power	1800KW/2250KVA
Standby Power	2000KW/2500KVA
Output Frequency / Rated speed	60Hz/1800rpm
Rated Voltage	230V/400V

Engine Make	Cummins ONAN UK
Engine Model	QSK60-G4
Alternator model	Stamford PI734E
Control System	DSE7320
Phase	Three

- (1) Prime power: The rating is available for an unlimited of annual operating hours in variable load applications, in accordance with ISO8528-1.A 10% overload is available for a period of 1 hour within 12-hour period of operation, in accordance with ISO 3046-1.
- (2) Standby power: The rating is applicable for supplying emergency power in variable load applications for up to 200 hours per year in accordance with ISO8528-1. Overload is not allowed.
- (3) Rated voltage: available with customer requirement.

#### Engine Specifications (DETAILED in APPENDIX)

Engine Model	QSK60-G4
Engine Manufacturer	Cummins
	ORIGINAL UK
Cylinder quantity	16
Cylinder Arrangement	60° Vee
Cycle	4

Aspiration	Turbo-charged
Bore x Stroke (mm x mm)	159×190
Displacement	60.2L
Compression Ratio	14.5:1
Prime power / Speed (KW/RPM)	1972kw/1800
Standby power/ Speed (KW/RPM)	2164kw/1800







## SHENZHEN FUDIANKANG ENERGY CO., LTD

Tel:86-13729889887 Fax:86-20-84550026

4		Web: www.fdkenergy.com E	mail: info@fdkenergy.com
Type Injection System	Cummins	Fuel Consumption at 100% load	196 at 1800rpm
	HPI-PT	(g/KWh)	
Piston Speed	11.5m/s	Starter motor	24V
Friction Energy Output	175kw	Low idle	700-900pm
Total Lubrication System Capacity	280L	Coolant Capacity (L)	157

#### **Alternator Specifications**

Alternator model	PI734E	Number of phase	3	
Alternator manufacturer	STAMFORD	Rated voltage	440V (Available with	
Exciter type	Single bearing, Brushless,		custom requirements)	
. <u> </u>	Self-excited	Power factor	0.8	
Rated output prime power	2300 KVA	Voltage regulation NL-FL	≤±1%	
Rated speed	1800 rpm	Insulation grade	Н	
Rated frequency	60Hz	Protection grade	IP23	

Alternator option: Leroy Somer, MECC, Marathon, Engga, Faraday

### Control System DSE7320 (DETAILED in INSTRUCTION)

DSE7320 is an advanced control module based on micro-processor, containing all necessary functions for protection of the genset and the breaker control. It can monitor the mains supply, breaker control and automatically start the engine when the mains are abnormal. Accurately measure various operational parameters and display all values and alarms information on the LCD. In addition, the control module can automatically shut down the engine and indicate the engine failure.

#### **FEATURES**

- Microprocessor control, with high stability and credibility.
- Monitoring and measuring operational parameters of the mains supply and genset.
- Indicating operation status, fault conditions, all parameters and alarms.
- Multiple protections; multiple parameters display, like pressure, temp. etc.
- Manual, automatic and remote work mode selectable.
- Real time clock for time and date display, overall runtime display, 250 log entries.
- Overall power output display.
- Integral speed/frequency detecting, telling status of start, rated operation, overspeed etc.
- Communication with PC via RS485 OR RS232 interface, using MODBUS protocol.

#### **Soundproof Enclosure Specification**

FDK silent generator is designed by professional acoustic engineers based on years of experience. Now we can make the noise of the generator less than 80-85dB(A) at 1m, or 70-75dB(A) at 7m, 60-65dB(A) at 15m.

#### **FEATURES**

- Multi-way air intake and exhaust guarantee the power performance of the generator.
- Large-scale impedance combined type silencer effectively reduce noise of the generator.
- Internal high performance rubber damper and flexible materials reduce vibration.
- Base mounted fuel tank supports the generator running for 8 hours.







# SHENZHEN FUDIANKANG ENERGY CO., LTD

Tel:86-13729889887 Fax:86-20-84550026

Web: www.fdkenergy.com Email: info@fdkenergy.com

#### Optional

Ger	erator set	Alte	rnator	Low	environment Temp	ATS	
	Open generator set		Stamford		Water heater		CHINT
	Silent generator set		Marathon		Oil heater		SCHNEIDER
	Trailer generator set		Mecc Alte		Battery heater		ABB
	ABB MCCB circuit breaker		Leroy Somer				
			Farady				
			Engga				
Fue	system	Con	trol system	Volta	age	Syn	chronized system
	12hrs base tank		AMF function		415/240V		CHINT Cabinet
	24hrs base tank		ATS control cabinet		400/230V		SCHNEIDER Cabinet
	Dual wall base fuel tank		DSE7320		380/220V		DSE8610 Module
	Outside fuel tank		DSE7510		220/127V		COMAQ Module
			GU620A		200/115V	П	DEIF Module

### **Dimension & Weight** Open

Overall Size:	5900×2100×2750
LxWxH (mm)	
Weight (kg)	16000

### **Soundproof Version**

Overall Size:	40FT CONTAINER		
LxWxH (mm)			
Weight (kg)	29000		

#### **Sales Promises**

- FDK provides a full line of brand new and high quality products. Each and every unit is strictly factory tested before shipment.
- Quality warranty is according to our standard conditions: 12 months from BL date or 1000 running hours, whichever comes
- Service and parts are available from FDK or distributors in your location.
- FDK guarantee use BRAND NEW & GENUINE MACHINE.



